


FollowMe: Ringing Multiple Locations Simultaneously

We have found that a typical use of FollowMe is to have an inbound call ring a desk phone, cell phone, home phone, any number of phones simultaneously. When configured correctly, the user will be able to answer at any of these locations and the caller will be unaware that the PBX is trying to contact the user at multiple locations.

- Edit the extension by clicking .
- Navigate to the Advanced area of the extension settings
- Under the **Follow-Me** panel click the **Numbers & Settings** button

Allow Codecs	Calling Permissions
<div> <div>G.723.1 G.726 iLBC Speex LPC10</div> <div> <div>G.711 (ulaw) G.711 (alaw) GSM</div> <div> <div>Up</div> <div>Down</div> </div> </div> <div> <div>Add</div> <div>Remove</div> </div> </div>	<div> <div>Allow User to control Forwarding</div> <div>✓</div> </div> <div> <div>Allow User to control Follow-Me</div> <div>✓</div> </div> <div> <div>Allow User to change Phone Key Settings</div> <div>✓</div> </div> <div> <div>Internal Calls</div> <div>✓</div> </div> <div> <div>Allow Incoming Intercom Paging</div> <div>✓</div> </div> <div> <div>Allow Outgoing Intercom Paging</div> <div>✓</div> </div> <div> <div>Allow User to Forward Calls</div> <div>✓</div> </div> <div> <div>Allow User to Record Calls</div> <div>✓</div> </div> <div> <div>Allow User to Listen to Others' Calls</div> <div>✓</div> </div> <div> <div>Allow User to Whisper</div> <div>✓</div> </div> <div> <div>Allow Others to Whisper</div> <div>✓</div> </div> <div> <div>Allow Others to Listen</div> <div>✓</div> </div> <div> <div>Allow Others to Record this User's Calls</div> <div>✓</div> </div> <div> <div>Allow Call Park</div> <div>✓</div> </div> <div> <div>Is Operator</div> <div><input type="checkbox"/></div> </div>

Follow-Me

Manage

Numbers & Settings

Figure 1 - Default FollowMe Settings

Options	
<input checked="" type="checkbox"/>	Play the Incoming message to Caller before starting search.
<input checked="" type="checkbox"/>	Record the Caller's name and play it to You.
<input checked="" type="checkbox"/>	Play the Unreachable message if You could not be found.
Add	12 seconds to total search time so Caller has time to listen & record.
Call From Prompt:	System Default
No Recording Prompt:	System Default
Options Prompt:	System Default
Please Hold Prompt:	System Default
Status Prompt:	System Default
Sorry Prompt:	System Default
Music On Hold	Use System Default

Numbers					
Use	Priority	Rings	Type	Name	Number
<input type="checkbox"/>	20	2	Mobile		
<input type="checkbox"/>	20	2	Mobile		
<input type="checkbox"/>	20	2	Mobile		
<input type="checkbox"/>	20	2	Mobile		
<input type="checkbox"/>	20	2	Mobile		
<input type="checkbox"/>	20	2	Mobile		
<input type="checkbox"/>	20	2	Mobile		
<input type="checkbox"/>	20	2	Mobile		

- Set **Add X seconds to total search time so Caller has time to listen & record** to 30sec (or more).
- Uncheck **Play the Incoming message to Caller before starting search.**
- Uncheck **Record the Caller's name and play it to You.**
- Uncheck **Play the Unreachable message if You could not be found.**
- Set the **Please Hold Prompt** and **Status Prompt** to **1-sec-silence.**
- Set the **Music on Hold** to **Ringin**g (you will have to create a MOH playlist called Ringing and load a sound file for ringing).
- Under **Numbers** enter a **Name** (arbitrary) and **Number** for each location you would like to be called.
- Ensure all of the **Numbers** to be called are set to the same **Priority.**
- Check the box next to each **Number** to be called so they are enabled for **Use.**
- Save the FollowMe settings.

Figure 2 - Configured FollowMe Settings

Administrator View - Follow-Me Settings / Extension 202

Options

☐
Play the Incoming message to Caller before starting search.

☐
Record the Caller's name and play it to You.

☐
Play the Unreachable message if You could not be found.

Add

seconds to total search time so Caller has time to listen & record.

Call From Prompt:

System Default

No Recording Prompt:

System Default

Options Prompt:

System Default

Please Hold Prompt:

1-sec-silence

Status Prompt:

1-sec-silence

Sorry Prompt:

System Default

Music On Hold

Ringing

Exit

Save

Numbers

Use	Priority	Rings	Type	Name	Number	
<input checked="" type="checkbox"/>	20	2	Mobile	Cell	1234567	
<input checked="" type="checkbox"/>	20	2	Home	Home	1234567	
<input checked="" type="checkbox"/>	20	2	Work	Desk	202	
<input type="checkbox"/>	20	2	Mobile			
<input type="checkbox"/>	20	2	Mobile			
<input type="checkbox"/>	20	2	Mobile			

- Edit the Extension settings in the PBX.
- Set Unconditional Forwarding to the FollowMe which was previously configured.
- Click

Save Changes
- Click **Apply Changes**

Forwarding Settings

Unconditional

Enabled

☐ Phone Number

☒ Destination

FollowMe

Follow-Me: 202

...

Busy

Disabled

No Answer

Disabled

Unavailable

Disabled

From this point on, any calls direct to this Extension will, via the FollowMe settings, call the Desk phone, Cell phone, and Home phone simultaneously. The caller will hear only ringing, and if the call goes unanswered they will leave a message in the Extension's Voicemail box.